

# TP45D2-A7 Motherboard



- Intel LGA775 Platform
- Support latest Intel Socket 775 Core 2 Extreme/Core 2 Quad/Core 2 Duo Processors
- Support Intel 45nm CPU processors
- Intel P45+ICH10 chipset
- FSB 1600(OC)/1333/1066
- Dual-Channel DDR2 -1066(OC)/800/667
- Solid Capacitors designed on CPU VRM area

## TP45D2-A7 Specification

CPU SUPPORT	Intel® Core™2 Extreme Processor Intel® Core™2 Quad Processor Intel® Core™2 Duo Processor Intel® Pentium® Dual-Core Processor Intel® Celeron® Dual-Core Processor Intel® Celeron® Processor 400 Sequence
FSB	Support FSB 800/1066/1333/1600(OC)MHz
MEMORY	Support Dual Channel DDR2 667/800/1066(OC) MHz 4 x DDR2 DIMM Memory Slot Max. Supports up to 16GB Memory
STORAGE	6 x SATA II Connector 1 x IDE Connector
LAN	Realtek RTL8111C - 10/100/1000 Controller
AUDIO CODEC	Realtek ALC662 6-Channel HD Audio
USB	6 x USB 2.0 Port 3 x USB 2.0 Header
EXPANSION SLOT	1 x PCI-E 2.0 x16 Slot 2 x PCI-E x1 Slot 3 x PCI Slot

REAR I/O	1 x PS/2 Mouse 1 x PS/2 Keyboard 6 x USB 2.0 Port 1 x LAN Port 3 x Audio Jacks	
INTERNAL I/O	3 x USB 2.0 Header 6 x SATA II Connector (3Gb/s) 1 x IDE Connector 1 x Floppy Connector 1 x Front Audio Header 1 x Front Panel Header 1 x CD-IN Header 1 x CPU Fan Connector 2 x System Fan Connector 1 x COM Port Header 1 x Printer Port Header	
DIMENSION	ATX Form Factor Dimension: 30.5 cm X 22 cm ( W x L )	
OS SUPPORT	Supports Windows 2000 / XP / Vista	
ACCESSORIES	1 x IDE Cable 2 x SATA Cable 1 x SATA Power Cable 1 x I/O Shield 1 x Fully Setup Driver CD 1 x User Manual	
FEATURES	Windows 7 Compatible Supports Solid capacitor Tweak Tech Supports Clean-Tone Supports O.N.E Supports Rapid Switch Supports Rapid Debug BIO-FLASHER Supports Toverclcoker OC software	
TP45D2	TP45D2-A7 OVERVIEW	

#### TP45D2-A7 OVERVIEW

## **CPU-Chipset**



## Intel P45 chipset

The Intel® P45 Chipset supports the latest multicore processors with FSB 1600MHz, plus the 45nm processors with record-breaking performance and greater energy efficiency. Intel® P45 chipset with optimized system memory capabilities and maximum overclocking, provides faster boot and application load times, as well as additional power saving advantage and scalable options for HD video and 3D gaming!



## FSB1600 Support

Based on Biostar's excellent Tseries design and reliable components, this motherboard native supports FSB 1600/ 1333 / 1066 / 800 MHz which allow you to enjoy the latest Intel technology backed by one of the most powerful CPUs in the world.

#### Audio+



## Clean Tone Technology

Biostar innovative low distortion audio design reduces high frequency noise generated by a motherboard. One independent capacitor per channel handles the occurring noise. Onboard 8+2 channel Realtek ALC 888CODEC features an HD audio solution. T-series delivers a signal to the noise ratio over 95dB which perfectly fits into the Windows Vista premium environment.

Speed+



## PCI Express 2.0 Support

PCI Express 2.0 bus architecture offers a futureproofing bridge to tomorrow's most bandwidthdriven games and 3D applications by maximizing 5 GT/s of bandwidth. PCI Express 2.0 motherboards are fully backwards compatible with existing PCI Express products for broad support of PC peripherals.



#### O M E

#### O.N.E

Biostar offers 3 kinds of overclocking settings (V6/V8/V12) that provide good, better, best O.C settings. The motherboard features the Biostar T series motherboards that allow users to conveniently load preset BIOS settings. These BIOS settings give users freedom to enjoy overclocking with simple instructions.



T-Overclocker

#### Tseries OC Utility

T-series OC utility presents the most convenient Windows-based system performance enhancement and utility management. Its 4 separate utilities include overclocking, BIOS update, and H/W monitoring and PC health for monitoring system status.



Tweek Tech

#### Tweak Tech

Biostar has a unique engineering PWM layout with low ESR and high ripple conductive solid state caps that provide sufficient, stable power supply to the CPU. The same philosophy applies to our DDR design to enhance the memory's voltage stability.

#### Durable+



X.D.C (eXtreme Durable Capacitors)

Biostar adopts low ESR and high ripple conductive solid state caps that provide sufficient, stable power supply to the CPU. The life span can also be more than 6.25 x of ordinary liquid caps.

#### DIY+



#### MX SUITE

As an Biostar customer you can download MAGIX multimedia tools designed to enhance your music, videos and photos for free. From music and website creation to video editing and photo management. Four products that cover all of your multimedia needs. Simply do more with your media than you ever thought possible.



#### Simplitec

"Simplitec" offers premium solutions to ensure your PC is faster, more reliable and free of security gaps - automatically or with customized setups. "Simplitec" is a free bundle software to scan your computer for problems and offers a professional solution for each problem to put your PC back in top form.



#### **BIO-Flasher**

BIO-Flasher is a convenient BIOS update tool. Just launch this tool and put the BIOS on USB pen driver before entering the OS. You can update your BIOS with only a few clicks without preparing an additional floppy disk or other complicated flash utility.



#### **BIO-ReLife**

BIO-ReLife Technology lets you recover crashed BIOS data from a USB flash pen driver that stores new BIOS file. This practical BIOS utility can restore your system and recover from a BIOS crash situation.

e HC	)T VE
LIN	JE)

eHot-Line Utiltiy

Integrated e-service automatically sends your technical support request to Biostar Globe tech support without any delay.



Rapid Switch

No more meddling with the power and reset jumpers onboard. The power and reset buttons are already built onboard. It is convenient for DIY users to test the board without short-circuiting the wrong pins.



Rapid Debug

There is no need to check any H/W installation error. Onboard LED indicator answers the question for the user.

\*The specification and pictures are subject to change without notice and the package contents may differ by area or your motherboard version!