

Hi-Fi A88S3+ Motherboard



- Supported Socket FM2+/FM2 processors AMD A-series/ E2-series processor
- Supported AMD Mutil Core(x4,x2)
- AMD 100W processor support
- AMD A88X Chipset
- 4 DIMM supported DDR3-2600(OC)/ 2400(OC)/ 2133/ 1866/ 1600/ 1333/ 1066/ 800
- Supported SATA 6Gb/s 2X speed than current SATA 3G
- Supported USB 3.0
- AMD Dual Graphics Technology
- BIOSTAR Puro Hi-Fi

Hi-Fi A88S3+ Specifcation

CPU SUPPORT	AMD A10 Processor AMD A8 Processor AMD A6 Processor AMD A4 Processor AMD E2 Processor AMD Athlon™ II X4 Processor Maximum CPU TDP (Thermal Design Power) : 100Watt
MEMORY	Support Dual Channel DDR3 2600(OC)/2400(OC)/2133/1866/1600/1333/1066/800 MHz 4 x DDR3 DIMM Memory Slot Max. Supports up to 64GB Memory
INTEGRATED VIDEO	By CPU model AMD Dual Graphics Technology Supports DX11.1 Supports HDCP
STORAGE	8 x SATA III Connector Support SATA RAID: 0,1,5,10
LAN	Realtek RTL8111G - 10/100/1000 Controller

AUDIO CODEC	Realtek ALC892 8-Channel Blu-ray Audio
USB	2 x USB 3.0 Port 1 x USB 3.0 Header 4 x USB 2.0 Port 2 x USB 2.0 Header
EXPANSION SLOT	1 x PCI-E 3.0 x16 Slot(supported by FM2+ CPU) 1 x PCI-E 2.0 x16 Slot(x4) 2 x PCI Slot
REAR I/O	1 x PS/2 Keyboard 2 x USB 3.0 Port 4 x USB 2.0 Port 1 x HDMI Connector 1 x DVI (Dual Link) Connector 1 x VGA Port 1 x LAN Port 6 x Audio Jacks
INTERNAL I/O	1 x USB 3.0 Header 2 x USB 2.0 Header 8 x SATA III Connector (6Gb/s) 1 x Front Audio Header 1 x Front Panel Header 1 x S/PDIF-Out Header 1 x CPU Fan Connector 2 x System Fan Connector 1 x CIR Header 1 x COM Port Header 1 x Printer Port Header
H/W MONITORING	CPU / System Temperature Monitoring CPU / System Fan Monitoring Smart / Manual CPU Fan Control System Voltage Monitoring
DIMENSION	Micro ATX Form Factor Dimension: 24.4cm x 23.5cm (W x L)
OS SUPPORT	Supports Windows XP / 7 / 8 / 10(x64)
BUNDLE SOFTWARE	BIO-Remote2 BIO-Remote Smart Speed LAN
ACCESSORIES	2 x SATA Cable 1 x I/O Shield 1 x DVD Driver 1 x Quick Guide

FEATURES	Supports PURO Hi-Fi Supports 100% Solid capacitor BIO-FLASHER Supports Charger Booster Supports BIOS Online Update
----------	--

Hi-Fi A88S3+ OVERVIEW

Audio+



Blu-ray Audio

Upgrading your Audio performance in the easiest way is choosing BIOSTAR ultimate Motherboard. It does support Blu-ray audio DRM (compatible driver/software) and provide the higher audio output of 24 bit/ 192KHz than the 16 bit/ 48KHz from the normal MB. You will experience the high quality sound effect with pure Blu-Ray Audio.



Hi-Fi Power

Audio power is an important factor in audio quality. Most AV equipment isolates the power supply for each analog and digital signal to gather high-quality sound reproduction. Equipped with BIOSTAR Hi-Fi Power technology, it will utilize audio components with independent power design for a significant reduction in electronic noise and superb sound quality.



Hi-Fi Ground

BIOSTAR Hi-Fi Ground (Golden Line) is noise-blocking multi-layer PCB design to isolates analog audio signals from digital sources. Unique PCB layout is ideal for exceptional clarity and high fidelity sound.



Hi-Fi Sound

BIOSTAR Hi-Fi series motherboards have a sampling rate of 192kHz/24-bit which delivers a high quality audio through an analog connection to your home theater system, multi-channel speakers and high-end headphone. You can enjoy real Blu-ray grade high-definition sound that you've never experienced before.



Hi-Fi AMP

The built-in amplifier can drive major high-end headphones with over 100dB loads and offer wide band-width, low noise, high slew rate and low distortion audio source from front panel I/O. Gaming enthusiasts can enjoy a fuller range of dynamic sound with crisper details and less distortion.



Smart Ear

Smart EAR is a windows-based audio utility which allows you to easily adjust system volume. With its user-friendly GUI, you can also increase or decrease impedance setting (Low/High Gain) to optimize your headphone performance. You can easily enjoy high-quality and awesome sound.



Hi-Fi Resistor

Metal-oxide film resistors are made of metal oxides such as tin oxide. The electric characteristics are greater stability and reliability than regular metal film resistors when operating in an extremely broad working temperature range. This special component is used in applications with high endurance audio demands.



Hi-Fi Cap

BIOSTAR Hi-Fi series motherboards come with high quality 'Non-Polarized Electrolysis Electric audio capacitors' for each audio channel circuit. The customized audio capacitors deliver low noise, low distortion, and wide bandwidth to achieve the highest sound resolution and sound expansion. The critical component will ensure the most realistic sound effects to gaming enthusiasts.



Hi-Fi 110dB+

Embrace exceptional sound quality for the win with 110dB SNR and stylish and efficient EMI shield blocks electromagnetic interference to help provide cleaner audio. It has achieved a signal-to-noise ratio (SNR) of 110dB, yielding almost loss-less audio form rear audio connectors.

Speed+



SmartSpeedLAN

SmartSpeedLAN is a free software application which monitors and manages your PC's network behavior. With user-friendly GUI, it allows you to select and prioritize different types of network traffic, including gaming, media streaming, communications or web surfing. You can also set any specific applications, choosing to prioritize or block accordingly. SmartSpeedLAN can feature automatic management options that use adaptive networking intelligence to ensure that you are getting the best online experience possible.



USB 3.0

Experience Fastest data transfers at 5 Gbps with USB 3.0--the new latest connectivity standard. Built to connect easily with next-generation components and peripherals, USB 3.0 transfers data 10X faster and backward compatible with previous USB 2.0 components.



Charger Booster

Charger booster is the best and efficient charger solution for apple devices such as iPad, iPhone. Basically, Charger booster Technology is able to boost the charging time to be more efficiency and faster once any apple goods connecting to our Motherboard. With charger booster technology, you are able to charge your apple devices up to 42 % faster.



SATAIII 6Gbps

SATAIII 6Gbps provides a higher bandwidth to retrieve and transfer HD media. With this super speed data transfer, SATAIII allows an incredible data boost which is 2x faster than the SATA II.

Durable+



100% Solid Caps

With armor-plated Biostar Technology, all capacitors are placed with 100% solid capacitors that have a lasting life cycle, durability and stability for crucial components.

Protection+



High Quality ESD

BIOSTAR Hi-Fi series motherboards provide high quality ESD (Electro-Static Discharge) solution for its front I/O panel. This function prevents static electricity and reduces the damage to the motherboards when you are plugging or unplugging your headphone.

DIY+



UEFI BIOS

Unified Extensible Firmware Interface (UEFI) is a brand new framework that provides a revolutionary interface. It is a modern clear and easy-to-use graphical user interface. The UEFI comes with a colorful easy-understand icons leads users into the setup layer directly.



BIO-Remote 2

BIO-Remote2 Technology is featuring users a better Home Theater environment. Users who own either Android mobile or Apple goods are able to access and control your PC remotely; At this moment, you're smart device became a intelligent and functional remote controller; more than that, BIO-Remote2 also includes both function of mouse pad and power point presentation mode.



Rapid Switch 2

Engineered by BIOSTAR, the exquisite onboard switches allow you to easily shut down and restart your system.



Rapid Debug 2

Rapid Debug 2

There is no need to check any H/W installation error. Onboard LED indicator shows 6 kinds of messages: CPU power, MB power, CPU, memory and PCI-E, SATA.

*The specification and pictures are subject to change without notice and the package contents may differ by area or your motherboard version!

BIOSTAR