

H61MGV3 Motherboard



- Socket LGA 1155
- Supported the Intel 3rd and 2nd generation Core i7/ i5/ i3 processors in the 1155 package
- Supported 2 DIMM of DDR3 1600/1333/1066MHz
- Supports BIO-Remote 2 Technology

H61MGV3 Specifcation

CPU SUPPORT	Intel® Core [™] i7 LGA 1155 Processor Intel® Core [™] i5 LGA 1155 Processor Intel® Core [™] i3 LGA 1155 Processor Intel® Pentium® LGA 1155 Processor Maximum CPU TDP (Thermal Design Power) : 95Watt
MEMORY	Support Dual Channel DDR3 1066/1333/1600 MHz 2 x DDR3 DIMM Memory Slot Max. Supports up to 16GB Memory
INTEGRATED VIDEO	By CPU model
STORAGE	4 x SATA II Connector
LAN	Realtek RTL8111G - 10/100/1000Mb/s Controller
AUDIO CODEC	Realtek ALC662 6-Channel HD Audio
USB	4 x USB 2.0 Port 2 x USB 2.0 Header
EXPANSION SLOT	1 x PCI-E 3.0 x16 Slot(supported by Core i5 -3xxx / Core i7 3xxx CPU) 1 x PCI-E 2.0 x1 Slot

REAR I/O	1 x PS/2 Mouse 1 x PS/2 Keyboard 4 x USB 2.0 Port 1 x VGA Port 1 x LAN Port 3 x Audio Jacks
INTERNAL I/O	2 x USB 2.0 Header 4 x SATA II Connector (3Gb/s) 1 x Front Audio Header 1 x Front Panel Header 1 x CPU Fan Connector 1 x System Fan Connector 1 x COM Port Header
H/W MONITORING	CPU / System Temperature Monitoring CPU / System Fan Monitoring Smart / Manual CPU Fan Control System Voltage Monitoring
DIMENSION	Micro ATX Form Factor Dimension: 19.1cm x 17cm (W x L)
OS SUPPORT	Supports Windows XP / Vista / 7 / 8
BUNDLE SOFTWARE	BIO-Remote2
ACCESSORIES	2 x SATA Cable 1 x I/O Shield 1 x DVD Driver 1 x Quick Guide
FEATURES	Windows 8 Ready BIO-FLASHER Supports Charger Booster Supports BIOS Online Update

H61MGV3 OVERVIEW

CPU-Chipset



Intel H61 chipset

The Intel® H61 Express Chipset is a single-chipset design to support the new 1155 socket Intel® 3rd/2nd Generation Core[™] i7 / Core[™] i5 / Core[™] i3 / Pentium® / Celeron® processors. It provides improved performance by utilizing serial point-t--point links, which allows increased bandwidth and stability.



Intel LGA 1155 3rd Generation Intel Core[™] Processor support

Intel 3rd generation processor "Ivy Bridge" is the codename for Intel's 22nm of the Sandy Bridge microarchitecture. The first to use tri-gate("3D") transistors, it is also backwards-compatible with the Sandy Bridge platform requiring a BIOS/firmware update.

Audio+







HD Audio

Provides high quality sound with minimal loss of audio fidelity.

SmartSpeedLAN

SmartSpeedLAN is a free software application which monitors and manages your PC's network behavior. With user-friendly GUI, it allows you to select and prioritize different types of network traffic, including gaming, media streaming, communications or web surfing.You can also set any specific applications, choosing to prioritize or block accordingly. SmartSpeedLAN can feature automatic management options that use adaptive networking intelligence to ensure that you are getting the best online experience possible.

Charger Booster

Charger booster is the best and efficient charger solution for apple devices such as iPad, iPhone. Basically, Charger booster Technology is able to boost the charging time to be more efficiency and faster once any apple goods connecting to our Motherboard. With charger booster technology, you are able to charge your apple devices up to 42 % faster.







PCIe 3.0

PCIe 3.0 is the ubiquitous and general-purpose PCI Express I/O standard. At 8GT/s bit rate, the interconnect performance bandwidth is doubled over PCIe 2.0, while preserving compatibility with software and mechanical interfaces.

Dual DDR3-1600

It supports 2 or 4 DIMM Slots DDR3 memory that features data transfer rates of DDR3 1600/1333. The processor support 2 memory channels and setting the memory multiplier, allows selection of the channel speed. These clearly uplift the band width and boost the overall system performance.

Durable+



Moistureproof of PCB

The popularity of PC usage and working environment is getting deteriorating and moist (rural, coastal, etc.). The PCB will be oxidizing easily by damp or absorbed moisture, and ionic migration or CAF (Conductive Anodic Filament) will be generated. Moisture-proof PCB meets high density and high reliability requirements for moisture proof.

Protection+




ESD Protection

ESD (Electrostatic Discharge) is the major factor to destroy the PC by electrical overstress (EOS) condition. ESD occurred by PC users when touch any devices connect to a PC, which may result in damage to the motherboard or parts. ESD protection is designed to protect the motherboard and equipment from damage by EOS.



USB Polyswitch

On board dedicated power fuse to help prevent USB port failure. It prevents USB Port overcurrent and safe guard your system and device lifespan.



OC / OV / OH Protection

OC / OV / OH Protection design detects overvoltage conditions and prevents voltage surges from spreading in real time. It also actively cuts off the overvoltage supply to protect your system.



DIY+





Header Zone

Users can easily assemble their own computer, a simple-swap data discs and other accessories.

BIO-Remote 2

BIO-Remote2 Technology is featuring users a better Home Theater environment. Users who own either Android mobile or Apple goods are able to access and control your PC remotely; At this moment, you're smart device became a intelligent and functional remote controller; more than that, BIO-Remote2 also includes both function of mouse pad and power point presentation mode.

BIO-Flasher

BIO-Flasher is a convenient BIOS update tool. Just launch this tool and put the BIOS on USB pen driver before entering the OS. You can update your BIOS with only a few clicks without preparing an additional floppy disk or other complicated flash utility.







eHot-Line Utiltiy

Integrated e-service automatically sends your technical support request to Biostar Globe tech support without any delay.

BIOScreen Utility

Personalize your desktop with customizable boot logo. BIOScreen is the new feature that lets you personalize and create your own style with unique, custom-made boot logo.

*The specification and pictures are subject to change without notice and the package contents may differ by area or your motherboard version!