

J1800NH2 Motherboard



- On board Intel Dual-core Celeron J1800(2.41GHz) processor
- Supports 2 SO-DIMM of DDR3L 1333MHz up to 16G maximum capacity
- Intel HD Graphics
- Mini ITX (17*17cm) for flexible use
- Supports BIO-Remote 2 Technology
- Supports Charger Booster Technology

J1800NH2 Specifcation

CPU	Intel® Celeron J1800(2.41GHz) Dual-Core Processor
MEMORY	Support Dual Channel DDR3L(1.35V/1.5V) 1333 MHz 2 x DDR3 SO-DIMM Memory Slot Max. Supports up to 16GB Memory The DIMM must be installed to DIMMA1 slot first.
INTEGRATED VIDEO	Intel HD Graphics Supports DX11 Supports HDCP
STORAGE	2 x SATA II Connector
LAN	Realtek RTL8111G - 10/100/1000Mb/s Controller
AUDIO CODEC	Realtek ALC662 6-Channel HD Audio
USB	1 x USB 3.0 Port 4 x USB 2.0 Port 1 x USB 2.0 Header
EXPANSION SLOT	1 x PCI-E 2.0 x1 Slot

REAR I/O	1 x PS/2 Mouse 1 x PS/2 Keyboard 1 x USB 3.0 Port 4 x USB 2.0 Port 1 x HDMI Connector 1 x VGA Port 1 x LAN Port 3 x Audio Jacks
INTERNAL I/O	1 x USB 2.0 Header 2 x SATA II Connector (3Gb/s) 1 x Front Audio Header 1 x Front Panel Header 2 x System Fan Connector 1 x COM Port Header 1 x Printer Port Header
H/W MONITORING	CPU / System Temperature Monitoring System Fan Monitoring System Voltage Monitoring
DIMENSION	Mini ITX Form Factor Dimension: 17cm x 17cm (W x L)
OS SUPPORT	Supports Windows 7 / 8 / 8.1 / 10(x64)
BUNDLE SOFTWARE	BIO-Remote2 Smart Speed LAN
ACCESSORIES	2 x SATA Cable 1 x I/O Shield 1 x DVD Driver 1 x Quick Guide
FEATURES	Supports Solid capacitor BIO-FLASHER Supports Charger Booster Supports BIOS Online Update
J1800NH2 OVERVIEW	
CPU-Chipset	



Intel Celeron J1800 Dual Core processor

The Intel® Celeron J1800(1M Cache, up to 2.58 GHz) is a dual-core processor. Although both parts are clocked the same, at 2.41 GHz, the J1800 also incorporates Burst Technology, that can boost operating frequency up to 2.58 GHz. The maximum GPU frequency was also increased on the J1800 to 792 MHz, while the base GPU speed stayed at 688 MHz. The rest of the specs have not changed. It supports DDR3L-1333 memory and fits into 10 Watt thermal envelope.

Audio+



HD Audio

Provides high quality sound with minimal loss of audio fidelity.

Video+



DX11

Direct3D 11 enables Direct3D 10 APIs and Direct3D 11 APIs to use one underlying rendering device. And it allows developers to achieve a high speed, fully conformant software rasterizer.



Integrated HDMI with HDCP

Onboard HDMI connector allows full video & audio support. It has industry-leading high definition video quality.

Speed+



SmartSpeedLAN

SmartSpeedLAN is a free software application which monitors and manages your PC's network behavior. With user-friendly GUI, it allows you to select and prioritize different types of network traffic, including gaming, media streaming, communications or web surfing. You can also set any specific applications, choosing to prioritize or block accordingly. SmartSpeedLAN can feature automatic management options that use adaptive networking intelligence to ensure that you are getting the best online experience possible.



USB 3.0

Experience Fastest data transfers at 5 Gbps with USB 3.0--the new latest connectivity standard. Built to connect easily with next-generation components and peripherals, USB 3.0 transfers data 10X faster and backward compatible with previous USB 2.0 components.



Charger Booster

Charger booster is the best and efficient charger solution for apple devices such as iPad, iPhone. Basically, Charger booster Technology is able to boost the charging time to be more efficiency and faster once any apple goods connecting to our Motherboard. With charger booster technology, you are able to charge your apple devices up to 42 % faster.

Durable+



Moistureproof of PCB

The popularity of PC usage and working environment is getting deteriorating and moist (rural, coastal, etc.). The PCB will be oxidizing easily by damp or absorbed moisture, and ionic migration or CAF (Conductive Anodic Filament) will be generated. Moisture-proof PCB meets high density and high reliability requirements for moisture proof.



Low RdsOn P-Pak MOS

Low resistance design can significantly reduce the current out of energy loss. Low temperature, small size, excellent thermal conductivity.



X.D.C (eXtreme Durable Capacitors)

Biostar adopts low ESR and high ripple conductive solid state caps that provide sufficient, stable power supply to the CPU. The life span can also be more than 6.25 x of ordinary liquid caps.

Protection+




ESD Protection

ESD (Electrostatic Discharge) is the major factor to destroy the PC by electrical overstress (EOS) condition. ESD occurred by PC users when touch any devices connect to a PC, which may result in damage to the motherboard or parts. ESD protection is designed to protect the motherboard and equipment from damage by EOS.



USB Polyswitch

On board dedicated power fuse to help prevent USB port failure. It prevents USB Port overcurrent and safe guard your system and device lifespan.



BIOS Virus Protection

When enabled, the BIOS will protect the boot sector and partition table by halting the system and flashing a warning message whether there's an attempt to write to these areas.



OC / OV / OH Protection

OC / OV / OH Protection design detects overvoltage conditions and prevents voltage surges from spreading in real time. It also actively cuts off the overvoltage supply to protect your system.



BullGuard Internet Security (90 days FREE trial)

BullGuard Internet Security comes with the broadest line-up of internet security features on the market, including: a cutting-edge dual Antivirus engine, Online Backup for your precious files, PC Tune Up to speed up your system, a Game Mode for a seamless gaming experience, Parental Control, Firewall, Safe Browsing and many more. Make the most of your digital life with Bullguard!

DIY+



BIO-Flasher

BIO-Flasher is a convenient BIOS update tool. Just launch this tool and put the BIOS on USB pen driver before entering the OS. You can update your BIOS with only a few clicks without preparing an additional floppy disk or other complicated flash utility.



BIOScreen Utility

Personalize your desktop with customizable boot logo. BIOScreen is the new feature that lets you personalize and create your own style with unique, custom-made boot logo.

***The specification and pictures are subject to change without notice and the package contents may differ by area or your motherboard version!**