

## Hi-Fi A68U3P Motherboard



- Supported Socket FM2+/FM2 processors AMD Aseries/ E2-series processor
- Supported AMD Mutil Core(x4,x2)
- AMD 100W processor support
- AMD A68H Chipset
- 2 DIMM supported DDR3-2600(OC)/ 2400(OC)/ 2133/ 1866/ 1600/ 1333/ 1066/ 800
- BIOSTAR Hi-Fi Technology
- AMD Dual Graphics Technology
- Supported Super LAN Surge Protection

# Hi-Fi A68U3P Specifcation

CPU SUPPORT	AMD A10 Processor AMD A8 Processor AMD A6 Processor AMD A4 Processor AMD E2 Processor AMD Athlon™ II X4 Processor Maximum CPU TDP (Thermal Design Power): 100Watt
MEMORY	Support Dual Channel DDR3 2600(OC)/2400(OC)/2133/1866/1600/1333/1066/800 MHz 2 x DDR3 DIMM Memory Slot Max. Supports up to 32GB Memory
INTEGRATED VIDEO	By CPU model AMD Dual Graphics Technology Supports DX11.1 Supports HDCP
STORAGE	4 x SATA III Connectors (6Gb/s) Support SATA RAID: 0,1,10
LAN	Realtek RTL8111G - 10/100/1000Mb/s Controller Support Super LAN Surge Protection
AUDIO CODEC	Realtek ALC662 6-Channel HD Audio

USB	2 x USB 3.0 Port 2 x USB 2.0 Port 2 x USB 2.0 Header
EXPANSION SLOT	1 x PCI-E 3.0 x16 Slot(supported by FM2+ CPU) 1 x PCI-E 2.0 x1 Slot 1 x PCI Slot
REAR I/O	1 x PS/2 Mouse 1 x PS/2 Keyboard 2 x USB 3.0 Port 2 x USB 2.0 Port 1 x HDMI Connector 1 x VGA Port 1 x LAN Port 3 x Audio Jacks
INTERNAL I/O	2 x USB 2.0 Header 4 x SATA III Connector (6Gb/s) 1 x Front Audio Header 1 x Front Panel Header 1 x CPU Fan Connector 1 x System Fan Connector 1 x COM Port Header
H/W MONITORING	CPU / System Temperature Monitoring CPU / System Fan Monitoring Smart / Manual CPU Fan Control System Voltage Monitoring
DIMENSION	Micro ATX Form Factor Dimension: 23.5cm x 17.8cm ( W x L )
OS SUPPORT	Supports Windows XP / 7 / 8 / 8.1 / 10(x64)
BUNDLE SOFTWARE	BullGuard BIO-Remote2 Smart Speed LAN
ACCESSORIES	2 x SATA Cable 1 x I/O Shield 1 x DVD Driver 1 x Quick Guide
FEATURES	Supports PURO Hi-Fi Supports 100% Solid capacitor BIO-FLASHER Supports Charger Booster Supports BIOS Online Update

# Hi-Fi A68U3P OVERVIEW

# **CPU-Chipset**



### AMD A68H chipset

AMD® A68H chipset is designed to support up to 5GT/s interface speed and PCI Express™ 3.0/2.0 graphics. It natively supports SATA 6Gb/s ports and USB 3.0 Ports.

### Audio+



#### Hi-Fi

A combination of exclusive hardware & software design including "ground-isolation circuit design", "an independent audio power", and "a built=on-board amplifier", with all these hardware features gives you the best audio quality and performance. As for software, we offer you a free bundle utility "Multi-Channel Calibration" which normally you'll find in high level sound systems; this feature allows you to auto detect your location; with a user friendly interface, you can easily adjust the volume of every speakers to make a well balanced surround sound. And of course, the built-on-board amplifier always gives you a super powerful sound comparing to other motherboards.



#### **HD** Audio

Provides high quality sound with minimal loss of audio fidelity.



### Hi-Fi Power

Audio power is an important factor in audio quality. Most AV equipment isolates the power supply for each analog and digital signal to gather high-quality sound reproduction. Equipped with BIOSTAR Hi-Fi Power technology, it will utilize audio components with independent power design for a significant reduction in electronic noise and superb sound quality.



#### Hi-Fi Ground

BIOSTAR Hi-Fi Ground (Golden Line) is noiseblocking multi-layer PCB design to isolates analog audio signals from digital sources. Unique PCB layout is ideal for exceptional clarity and high fidelity sound.



#### Hi-Fi Sound

BIOSTAR Hi-Fi series motherboards have a sampling rate of 192kHz/24-bit which delivers a high quality audio through an analog connection to your home theater system, multi-channel speakers and highend headphone. You can enjoy real Blu-ray grade high-definition sound that you've never experienced before.



#### Hi-Fi AMP

The built-in amplifier can drive major high-end headphones with over 100dB loads and offer wide band-width, low noise, high slew rate and low distortion audio source from front panel I/O. Gaming enthusiasts can enjoy a fuller range of dynamic sound with crisper details and less distortion.



#### **Smart Ear**

Smart EAR is a windows-based audio utility which allows you to easily adjust system volume. With its user-friendly GUI, you can also increase or decrease impedance setting (Low/High Gain) to optimize your headphone performance. You can easily enjoy high-quality and awesome sound.



#### Hi-Fi Resistor

Metal-oxide film resistors are made of metal oxides such as tin oxide. The electric characteristics are greater stability and reliability than regular metal film resistors when operating in an extremely broad working temperature range. This special component is used in applications with high endurance audio demands.



#### Hi-Fi Cap

BIOSTAR Hi-Fi series motherboards come with high quality 'Non-Polarized Electrolysis Electric audio capacitors' for each audio channel circuit. The customized audio capacitors deliver low noise, low distortion, and wide bandwidth to achieve the highest sound resolution and sound expansion. The critical component will ensure the most realistic sound effects to gaming enthusiasts.



#### Hi-Fi 110dB+

Embrace exceptional sound quality for the win with 110dB SNR and stylish and efficient EMI shield blocks electromagnetic interference to help provide cleaner audio. It has achieved a signal-to-noise ratio (SNR) of 110dB, yielding almost loss-less audio form rear audio connectors.

### Video+



#### DX11.1

Direct3D 11.1 enables Direct3D 10 APIs and Direct3D 11 APIs to use one underlying rendering device. And it allows developers to achieve a high speed, fully conformant software rasterizer.

### Speed+



### **SmartSpeedLAN**

SmartSpeedLAN is a free software application which monitors and manages your PC's network behavior. With user-friendly GUI, it allows you to select and prioritize different types of network traffic, including gaming, media streaming, communications or web surfing. You can also set any specific applications, choosing to prioritize or block accordingly. SmartSpeedLAN can feature automatic management options that use adaptive networking intelligence to ensure that you are getting the best online experience possible.



#### **USB 3.0**

Experience Fastest data transfers at 5 Gbps with USB 3.0--the new latest connectivity standard. Built to connect easily with next-generation components and peripherals, USB 3.0 transfers data 10X faster and backward compatible with previous USB 2.0 components.



### **Charger Booster**

Charger booster is the best and efficient charger solution for apple devices such as iPad, iPhone. Basically, Charger booster Technology is able to boost the charging time to be more efficiency and faster once any apple goods connecting to our Motherboard. With charger booster technology, you are able to charge your apple devices up to 42 % faster.

### Durable+



### Moisture proof of PCB

The popularity of PC usage and working environment is getting deteriorating and moist (rural, coastal, etc.). The PCB will be oxidizing easily by damp or absorbed moisture, and ionic migration or CAF (Conductive Anodic Filament) will be generated. Moisture-proof PCB meets high density and high reliability requirements for moisture proof.



#### Low RdsOn P-Pak MOS

Low resistance design can significantly reduce the current out of energy loss. Low temperature, small size, excellent thermal conductivity.

### Protection+



### **Super LAN Surge Protection**

Super LAN Surge Protection, providing LAN port with more advanced antistatic protection capabilities by adding an integrated chip to strengthen electrical stability and prevent damage from lightning strikes and electrical surges. SLSP (Super LAN Surge Protection) series motherboard upgrades the existing system protection standards with maximum 4X protection comparing to other board makers.



#### **ESD Protection**

ESD (Electrostatic Discharge) is the major factor to destroy the PC by electrical overstress (EOS) condition. ESD occurred by PC users when touch any devices connect to a PC, which may result in damage to the motherboard or parts. ESD protection is designed to protect the motherboard and equipment from damage by EOS.



### **USB Polyswitch**

On board dedicated power fuse to help prevent USB port failure. It prevents USB Port overcurrent and safe guard your system and device lifespan.





#### **BIOS Virus Protection**

When enabled, the BIOS will protect the boot sector and partition table by halting the system and flashing a warning message whether there's an attempt to write to these areas.



### OC / OV / OH Protection

OC / OV / OH Protection design detects overvoltage conditions and prevents voltage surges from spreading in real time. It also actively cuts off the overvoltage supply to protect your system.





#### **UEFI BIOS**

Unified Extensible Firmware Interface (UEFI) is a brand new framework that provides a revolutionary interface. It is a modern clear and easy-to-use graphical user interface. The UEFI comes with a colorful easy-understand icons leads users into the setup layer directly.



#### Header Zone

Users can easily assemble their own computer, a simple-swap data discs and other accessories.





BIO-Remote2 Technology is featuring users a better Home Theater environment. Users who own either Android mobile or Apple goods are able to access and control your PC remotely; At this moment, you're smart device became a intelligent and functional remote controller; more than that, BIO-Remote2 also includes both function of mouse pad and power point presentation mode.



### **BIOScreen Utility**

Personalize your desktop with customizable boot logo. BIOScreen is the new feature that lets you personalize and create your own style with unique, custom-made boot logo.

\*The specification and pictures are subject to change without notice and the package contents may differ by area or your motherboard version!