

H110MDE Motherboard



- Supports 7th Generation Intel® Core $^{\text{m}}$ Processor
- Intel H110 single chip architecture
 Support 2-DIMM DDR4-1866/ 2133/2400 up to 32G maximum capacity
- Support USB 3.1 Gen1
- Support DVI display port
- Support GbE LAN

Specifcation	
CPU SUPPORT	7th & 6th Gen Intel® Core™ i7 LGA 1151 Processor 7th & 6th Gen Intel® Core™ i5 LGA 1151 Processor 7th & 6th Gen Intel® Core™ i3 LGA 1151 Processor 7th & 6th Gen Intel® Pentium® LGA 1151 Processor 7th & 6th Gen Intel® Celeron® LGA 1151 Processor Maximum CPU TDP (Thermal Design Power) : 91Watt
MEMORY	Support Dual Channel DDR4 1866/ 2133/2400 MHz 2 x DDR4 DIMM Memory Slot Max. Supports up to 32GB Memory ** DDR4 2400 for 7th Generation Intel® Core™ Processor Family
INTEGRATED VIDEO	By CPU model Supports DX12 Supports HDCP
STORAGE	4 x SATA III Connector
LAN	Realtek RTL8111G - 10/100/1000Mb/s Controller
AUDIO CODEC	Realtek ALC662 6-Channel HD Audio
USB	2 x USB 3.1 Port 1 x USB 3.1 Gen1 Header 2 x USB 2.0 Port 2 x USB 2.0 Header
EXPANSION SLOT	1 x PCI-E 3.0 x16 Slot 1 x PCI-E 2.0 x1 Slot
REAR I/O G	1 x PS/2 Keyboard/Mouse 2 x USB 3.1 Port 2 x USB 2.0 Port 1 x DVI-D Connector, resolution up to 1920 x 1200 @60Hz 1 x VGA Port, resolution up to 1920 x 1200 @60Hz 1 x LAN Port 3 x Audio Jacks

INTERNAL I/O	1 x USB 3.1 Gen1 Header 2 x USB 2.0 Header 4 x SATA III Connector (6Gb/s) 1 x Front Audio Header 1 x Front Panel Header 1 x CPU Fan Connector
H/W MONITORING	CPU / System Temperature Monitoring CPU / System Fan Monitoring Smart / Manual CPU Fan Control System Voltage Monitoring
DIMENSION	Micro ATX Form Factor Dimension: 215mm x 170mm (W x L)
OS SUPPORT	Supports Windows Windows 7/ 8.1(64bit)/10(64bit) - 7th Core only support Windows 10)
BUNDLE SOFTWARE	BullGuard Smart Speed LAN
ACCESSORIES	2 x SATA Cable 1 x I/O Shield 1 x DVD Driver 1 x Quick Guide
FEATURES	Supports 100% Solid capacitor Supports Charger Booster Supports BIOS Online Update

OVERVIEW



Intel H110 chipset

The Intel® H110 chipset is a single-chipset design to support socket 1151 Intel® 6th generation Intel® Core™ processor-based platform. Provides excellent performance and increased bandwidth and stability. Intel® H110 chipset can also enable iGPU function, letting users enjoy the latest Intel® integrated graphic performance. The PC platform features improved adaptive performance that adds speed when you need it. When combined with advanced system responsiveness, the platform delivers the ultimate PC experience.



HD Audio

Provides high quality sound with minimal loss of audio fidelity.



DVI

DVI is better than VGA for LCD displays since it is digital while VGA is analog. For LCD displays, the picture is digitized pixel per pixel. Through DVI, the panel gets data for each pixel, so the picture generated in the Graphics device matches the pixels on the panel itself.



DX12

DirectX 12 introduces the next version of Direct3D, the graphics API at the heart of DirectX. Direct3D is one of the most critical pieces of a game or game engine, and we've redesigned it to be faster and more efficient than ever before. Direct3D 12 enables richer scenes, more objects, and full utilization of modern GPU hardware.



USB 3.1 Gen 1 Type-A

Experience Fastest data transfers at 5 Gbps with USB 3.1 Gen 1--the new latest connectivity standard. Built to connect easily with next-generation components and peripherals, USB 3.1 Gen 1 transfers data 10X faster and backward compatible with previous USB 2.0 components.



PCle 3.0

PCIe 3.0 is the ubiquitous and general-purpose PCI Express I/O standard. At 8GT/s bit rate, the interconnect performance bandwidth is doubled over PCIe 2.0, while preserving compatibility with software and mechanical interfaces.



Dual DDR4

The primary advantages of DDR4 over DDR3, include higher module density, lower voltage requirements, coupled with higher data transfer rate.



Moisture proof of PCB

The popularity of PC usage and working environment is getting deteriorating and moist (rural, coastal, etc.). The PCB will be oxidizing easily by damp or absorbed moisture, and ionic migration or CAF (Conductive Anodic Filament) will be generated. Moisture-proof PCB meets high density and high reliability requirements for moisture



Low RdsOn P-Pak MOS

Low resistance design can significantly reduce the current out of energy loss. Low temperature, small size, excellent thermal conductivity.



Super Anti-Surge Protection

BIOSTAR exclusive Anti-Surge design provides the best protection of board and extends the product life. Having the latest model of "Transient Voltage Suppressor" on- board can effectively protect the board circuit, reducing the shocks caused by ESD as well as other damages arising from overvoltage transients to enhance system durability.



Super LAN Surge Protection

Super LAN Surge Protection, providing LAN port with more advanced antistatic protection capabilities by adding an integrated chip to strengthen electrical stability and prevent damage from lightning strikes and electrical surges. SLSP (Super LAN Surge Protection) series motherboard upgrades the existing system protection standards with maximum 4X protection comparing to other board makers.



ESD Protection

ESD (Electrostatic Discharge) is the major factor to destroy the PC by electrical overstress (EOS) condition. ESD occurred by PC users when touch any devices connect to a PC, which may result in damage to the motherboard or parts. ESD protection is designed to protect the motherboard and equipment from damage by EOS.



USB Polyswitch

On board dedicated power fuse to help prevent USB port failure. It prevents USB Port overcurrent and safe guard your system and device lifespan.







BIOS Virus Protection

When enabled, the BIOS will protect the boot sector and partition table by halting the system and flashing a warning message whether there's an attempt to write to these areas.



OC / OV / OH Protection

OC / OV / OH Protection design detects overvoltage conditions and prevents voltage surges from spreading in real time. It also actively cuts off the overvoltage supply to protect your system.



Header Zone

Users can easily assemble their own computer, a simple-swap data discs and other accessories.

*The specification and pictures are subject to change without notice and the package contents may differ by area or your motherboard version!



